

Three Phase Hybrid Inverter

SUN-8/10/12K-SG05LP3-EU-SM2



100

100% unbalanced output, each phase; Max. output up to 50% rated power



AC couple to retrofit existing solar system

10

Max. 10 pcs parallel for on-grid and off-grid operation; Support multiple batteries parallel

240

Max. charging/discharging current of 240A

48

48V low voltage battery, transformer isolation design

6

6 time periods for battery charging/discharging



Support storing energy from diesel generator

Deye

Stock Code: 605117.SH

Model			
Battery Input Data			
Battery Type	Lead-acid or Lithium-ion		
Battery Voltage Range (V)	40-60		
Max. Charging Current (A)			
Max. Discharging Current (A)			
Charging Strategy for Li-ion Battery	Self-adaption to BMS		
Number of Battery Input	1		
PV String Input Data			
	12000		
		800	
Start-up Voltage (V)	160		
	200-650		
	550		
	20+20		
	30+30		
No. of MPP Trackers/ No. of Strings per MPP Tracker	2/1+1		
AC Input/Output Data			
Rated AC Input/Output Active Power (W)			
Max. AC Input/Output Apparent Power (VA)			
Rated AC Input/Output Current (A)			
Max. AC Input/Output Current (A)			
Max. Three-phase Unbalanced Output Current (A)			
Max. Continuous AC Passthrough (grid to load) (A)	45		
Peak Power (off-grid) (W)	2 times of rated power, 10s		
Power Factor Adjustment Range	0.8 leading to 0.8 lagging		
Total Current Harmonic Distortion THDi	<3% (of nominal power)		
DC Injection Current	<0.5% In		
Efficiency			
Max. Efficiency	97.6%		
Euro Efficiency	97.0%		
MPPT Efficiency	>99%		
Equipment Protection			
Integrated	DC Polarity Reverse Connection Protection, AC Output Overcurrent Protection AC Output Overvoltage Protection, AC Output Short Circuit Protection, Thermal Protection DC Terminal Insulation Impedance Monitoring, DC Component Monitoring, Ground Fault Current Monitoring Power Network Monitoring, Island Protection Monitoring, Earth Fault Detection, DC Input Switch Overvoltage Load Drop Protection, Residual Current (RCD) Detection, Surge protection level		
Surge Protection Level	TYPE II(DC), TYPE II(AC)		